

It runs with
the Sun

PowerCom



Be Smart Be Green

Solar FM/AM RADIO

Product Description

1. Support **solar** charging;
2. With small power bank to charge mobile phone;
3. Can play **MP3/WMA music** from **TF** card and **USB** flash drive (MAX 16G);
4. With **FM** radio, radio can automatically **scan** and **memory** channels;
5. With **3.5mm audio** line in jack, can easily and perfectly to connect to your **computer, MP3, MP4, mobile phones, iphones, PSP, etc;**
6. With standard **3.5mm full range earphone** jack, available for **earphones** to listen to radio and music;
7. With **LCD** synchronous **lyrics** display, can show **time** and **number** of songs, support **Chinese and English languages;**
8. Be available to **select** radio channels and music with 0-9 number buttons. it is user-friendly;
9. With **music repeating** function, can control to repeat the current ONE/FOLD/ALL;
10. Can set definite time of 30, 60, 120, 240 minutes to shutdown the product;
11. Can memory radio channels and delete radio channels manually;
12. If the battery of this product has power inside, then this product can be used as power bank in emergency situation;
13. With a **rechargeable BL-5C Lithium battery**, can charge by solar, connecting USB charging cable to computer or USB power adapter, or by universal charger, etc;
14. Charging indicator will turn green after fully charged;
15. With battery power balance display ;



www.powercom.com.bd

PowerCom
YOUR POWER CONSULTANT

It runs with
the Sun

16. In TF or USB mode, when power off, can **playback** the **current one music** when power on next time;
17. With UV coating surface.

Specifications

- (1) Input power: 5V
500MA
- (2) Maximum output:
3W
- (3) Battery capacity:
800mAh (marked 1000mAh) rechargeable BL-5C battery
- (4) Signal to Noise:
87dB
- (5) Decoding format:
MP3 (8-320Kbps)
- (6) Frequency
response: 150HZ-
18KHZ
- (6) FM radio: 87.5-
108MHz;
- (7) Internal magnetic
loud dual voice coil
peaker: 40MM 4ohms
3W
- (8) DC charging time: 3-5 hours
- (9) Solar charging time: 6-8 hours in strong sunshine
- (10) Light and electricity conversion rate: 10%-15%
- (11) Solar conversion power: 0.8W
- (12) Play time: 3-10 hours
- (13) Size: L126*W27*H74.5mm



PowerCom
YOUR POWER CONSULTANT

Power Control & Management

BSCIC Electronics Complex, Level-8
1/1 Industrial, Plot, Main Road-03
Avenue - 04, Section - 07, Mirpur
Dhaka-1216. Bangladesh.



Tel : +88-02-9014710, 8035077
Fax : +88-02-9035838
E-mail: info@powercom.com.bd
Web : www.powercom.com.bd

Hotline : +88 01712 611466